

KEY FEATURES

- Fully complies to IS 2189 & tested by ERTL(N)
- Operates on 220V AC, 50Hz AC Supply with battery backup & inbuilt charger
- Fire/fault status in unambiguous colored LED indications
- 128 Events logging facility with real time clock and keypad (optional)
- 0-3 minute time delay facility for auto release and manual release
- 2 mode of operation (AUTO/MANUAL) & Auto dialer attachable facility
- Common hooter output with individual zone and cross zone output
- Zone wise fire, open, short LED Indications
- Zone wise hooter output & Relay for free contacts
- External s/w to test each zone fire, open, short status manually
- External s/w for reset, Silence, Lamp test
- Zone isolation facility with zone voltage cutoff
- Mains on, system on, charger on visual indications
- Compatible with all types of fire detectors with max. 25 nos. in each zone
- Two zone with 1 no. flooding module, Four zone with 2 no. flooding module
- Use for various gas release system i.e. Fe 227, INERGEN, CO2, Fm200
- battery low & common fire indications
- 16*2 line dot matrix LCD (20*4 LCD optional)
- Separate monitoring of MRU & MAU
- LCD indication for timer on gas discharge

TECHNICAL DATA

- Operating Voltage	AC 220v 50Hz ±10%, DC 24v 1 amp
- Operating Temperature	0°C to 50°C
- Operating Humidity	95% (non-condensing)
- Hooter Output	2 A (24v DC)
- Solenoid valve output	2 A (24v DC)
- EOL	4k7 ohm, 1 per zone
- Weight	5.2 kg
- Construction	1.8 mm CRCA sheet duly power coated
- Dimension	H 362mm * W 403mm * D 122mm
- Colour	Caramel White

KEY FEATURES

- Operates on 220V AC, 50Hz AC Supply
- 16*2 line dot matrix LCD
- Battery backup with inbuilt charger + Relay for free contacts
- Operates on both tone and pulse + User password protection
- Speech dialer with 06 telephone nos. and 02 message
- 30 sec. duration time of message and Hooter time 0 to 7 min
- Real Time Clock with 128 event logging facility
- LCD display current date and time with current status of all zone
- Automatic and manual operation facility for security zone
- LCD and LED indication for open and alarm for security zone
- Zone naming facility for both fire and security zone
- Programmable exit/entry delay (01-03 min) in night zone
- Programmable hooter trigger delay (0 - 09 min)
- Entered telephone nos. and messages check facility
- Operates on both DOT and EPABX + Telephone nos. editing facility
- All programming and enter telephone nos. through keypad
- Programmable redial option (01 - 03 times)
- Fire/fault status in unambiguous colored LED indications
- Zone wise fire, open, short LED Indications
- External s/w to test each zone fire, open, short status manually
- Zone isolation facility with zone voltage cutoff
- Mains on, system on, charger on visual indications
- battery low & common fire indications
- Enough inside space for SMF battery
- Attachable with all types of fire detectors
- Maximum 25 nos. detectors in each zone

02 & 04 ZONE GAS SUPPRESSION PANELS



MODEL NO. : QT 02QGSP



MODEL NO. : QT 04QGSP

06 ZONE INTRUDER ALARM PANEL



MODEL NO. : QT PNB-FSD

TECHNICAL DATA

- Operating Voltage	AC 220v 50Hz ±10%, DC 24v 1 amp
- Operating Temperature	0°C to 50°C
- Operating Humidity	95% (non-condensing)
- Construction	1.8 mm CRCA sheet duly power coated
- Dimension	H 275mm * W 345mm * D 96mm
- Colour	Caramel White
- Hooter Output	1 A (24v DC)
- EOL	4k7 ohm, 1 per zone
- Weight	4.5 kg

